

# DHAL125ULX

## 1 AMP POWER SUPPLY/CHARGER



**Batteries Sold Separately**

AL125ULX is a Two (2) Output Switching power Supply/Charger that converts a 115VAC 50/60Hz input, into a two (2) individually PTC protected 12VDC or 24VDC outputs.



### Specification

- Input:** 115VAC, 50Hz/60Hz, 0.6 amp  
Access control trigger input
- Output:** 12VDC or 24VDC selectable output @ 1 amp
- Output Type:** Two (2) Class 2 Rated power limited outputs  
1. Fail-Safe/Fail-Secure lock output (switched).  
2. Auxiliary power output (unswitched).
- Features**
- Filtered and electronically regulated output
  - PTC protected outputs
  - Short circuit and thermal overload protection
  - Supervised Fire Alarm Disconnect (latching w/ reset or non-latching)
  - AC power and unit status indicator on front panel
- Enclosure:** 13.5"H x 13"W x 3.25"D  
Grey painted steel with key lockable cam lock  
Accommodates (2) 12VDC/7 AH batteries
- Battery Backup:** Built-in charger for sealed lead acid or gel type batteries (batteries sold separately)  
Automatic switch over to stand-by battery when AC fails  
Maximum charge current 0.4 amp
- Warranty:** Limited Lifetime warranty