

ALK-2000 EXIT ALARM KIT



The 2000 Series Exit Alarm Kit is a retrofit kit used to help prevent unauthorized use of an emergency exit door



Specification

- Application:** 2000 series rim exit devices, panic or fire rated
- Operation:** Alarm is armed/disarmed by turning key in the mortise cylinder
LED flashes green every 30 seconds to indicate alarm is in armed position
Alarm is activated when push bar is depressed
- Bypass:** Alarm can be bypassed by trim/key from the outside
- Battery:** 9 Volt battery included, life approximately 1 year - Low battery alert indicated by red flash & chirp every 5 seconds
- Decibel Rating:** Approximately 90 decibels at 15 feet
- Part Numbers:** ALK-2000 33" for standard length devices & ALK-2000 42" for long devices
- Included Parts:** New Slide Cover with LED indicator, Alarm Board, Mounting Plate, Mortise Cylinder, Cylinder Collar, Back Plate, Cylinder Retaining Ring, 9 Volt Battery, "Emergency Exit" Sticker for touchpad or door face
- Cylinders:** 1 1/8" Mortise cylinder with std. cam (included) - 6 Pin Brass, C Kwy, with 2 Keys
1 3/8" Mortise cylinder housing for 6 or 7 pin Small format IC core (less core)
- Finishes:** AL, BZ and GLD Painted & US32D
- Warranty:** Limited lifetime warranty